



# AIR BAND VHF Handheld Transceiver

## IC-A25CE

### Features

- 25 kHz channel Spacing
- 1500 mW loud audio provides clear communications
- 6 W (PEP) output power
- Up to 17 hours of long battery life
- IP57 dust-protection and waterproof construction
- LCD and key backlight for night time operation
- Compatible with third-party aviation headsets
- Auto Noise Limiter (ANL) for noise reduction
- Side Tone function
- Internal VOX capability
- 300 memory channels with 12 character names
- BNC type antenna connector



### Supplied Accessories

BP288 Battery, BC224 rapid charger, BC123SV AC adapter, FAB02AR antenna, MB133 Belt Clip & Hand Strap.

Order Code	Description
IC-A25CE	Handheld VHF AIR Band Transceiver (COM Channels & No Navigation)
<b>Batteries</b>	
BP288	Li-Ion battery: 7.2V 2200mAh (min) 2350 mAh (typ.) Waterproof.
BP289	Battery case: 6 x AA cell batteries required
<b>Chargers</b>	
BC224	Rapid Charger includes BC-123SV
BC123SV	AC Adapter for Straight plug type
CP20	Cigarette Lighter Cable to operate from a 12V or 24V DC power source
<b>Spare Antenna</b>	
FAB02AR	Antenna
<b>Belt Clips &amp; Hangers</b>	
MB133	Belt Clip- Alligator Type
MB96N	Swivel type belt hanger
MB96F	Fixed type leather belt hanger
MB96FL	Belt Hanger - Longer Type
<b>Hand Microphone &amp; Remote Audio Options</b>	
HM231	Speaker microphone (Waterproof)
<b>Headset Adaptor</b>	
OPC-2379	Headset Adapter cable for use with third party headset
<b>Programming Equipment</b>	
CS-A25	Dealer programming software: OPC-2144 and OPC- 478UC required
OPC-2144	Slim L-Type plug adapter cable
OPC-478UC	USB type radio programming Cable